OWNERS MANUAL

"Ivan IRONMAN Stewart's
SUPER OFF-ROAD "TM
TABLE OF CONTENTS

SECTION		PAGE
A.	GENERAL GAME INFORMATION	
	1. Game Concept	1
	2. Assembly Instructions	2
	3. Warranty Information	4
	4. Maintenance and Upkeep Procedures	5
C.	THE TROUBLESHOOTISTS SECTION	
	1. A Note About Power	6
	2. Our Service Department	6
	3. Troubleshooting Flow Chart	7
	4. General Shooting	8
	5. Monitor Shooting	8
	6. Buffers	8
	7. About Mechanical Coin Counters	9
D.	ILLUSTRATED PARTS LIST	
	1. Cabinet	10
	2. Controls (buttons, foot pedals, steering wheels, etc.)	11
E.	WIRING DIAGRAMS	
	1. Main Board	12
	2. Multi-Function Board	14
	3. Cabinet	16
F.	BOOKKEEPING AND DIAGNOSTICS SECTION	
	1. Main Menu - Bookkeeping - Diagnostics Menu	17
	2. Video Alignment Screens	21
	3. Game Set-Up - Game Statistics	23
E.	SCHEMATICS & BOARD LAYOUTS	
	1. Multi-Function Board Layout (top board)	27
	3. Multi-Function Board Schematics	28
	4. Main Board Layout (bottom board)	38
	5. Main Board Schematics	39
	6. 25" Wells Gardner Monitor	58

"Ivan IRONMAN Stewart's *SUPER OFF ROAD*"™ GAME CONCEPT

In his never ending quest for adventure and excitement, man invented off-road racing. These races were then brought before the masses by converting huge sports stadiums into dirt and mud obstacle courses in which off-road "Ironmen" battled for top honors.

Now **THE LELAND CORPORATION** brings this fast moving, hard driving sport to the video game arena.

"Ivan IRONMAN Stewart's *SUPER OFF-ROAD*"™ is stadium off-road racing at it's best. One to three players are asked to test their dirt track skills against the best dirt truck driver in the world.

Contestants compete on 8 different tracks with a total of 16 configurations and these courses are packed with enough jumps, bumps, hills, and holes to challenge even the most skillful driver.

Winning drivers earn "cash" prizes, and use this "cash" to "buff out" their machines. At the end of each race, players take their trucks to the "Speed Shop" to buy better shocks, tires, engines, and higher top speed. They can also buy nitro packs to help them blast over the jumps and through the mud.

The **"Convert-a-Credit"™** feature allows drivers to add to their winnings by using credits as "cash". Each additional quarter, when converted, becomes $200,000.00 in game "cash" and this additional "cash" may be used for purchases in the "Speed Shop".

Team Leland's **"Ivan IRONMAN Stewart's *SUPER OFF-ROAD*"™** has the depth and variety to be an income 'winner' for years to come.

"Ivan IRONMAN Stewart's
SUPER OFF-ROAD"™
CABINET ASSEMBLY ILLUSTRATION



ASSEMBLY INSTRUCTIONS

1. Remove all parts from shipping containers and check them for damage. Notify your distributor (and the shipper) **immediately** if you find any broken parts.
2. Detach and remove the pedal assembly from the inside of the main cabinet. Remove the two bolts **(A)** and blocks **(B)** from the bottom front of the main cabinet.
3. At this point, it is a good idea to lift the monitor plex and clean or dust from the monitor any debris which may have settled in shipment.
4. Remove the center (yellow) steering section from the control panel assembly by reaching through the hole in the bottom of the assembly and unfastening the three clips inside. Attach the monitor plex retainer **(C)** to the control panel assembly. (The wing nut should be loose until the control panel assembly has been attached to the game cabinet.)
5. Position the control panel with the harness connectors hanging into the main cabinet and secure the panel to the main cabinet by reaching through the front door and attaching the four clips provided.
6. Connect the control panel harness to the main harness, tighten the wing nut on the monitor plex retainer and reinstall the center steering section.
7. Feed the pedal harness through the center hole in the lower part of the cabinet and attach the pedal assembly using the bolts **(A)** and blocks **(B)** removed in step 2. ***REMOVE THE PEDAL ASSY. WHEN TRANSPORTING THE GAME.***
8. Check through the cabinet for loose wires. Plug the game in and power-up. Check for smoke.
9. Go through <u>all</u> diagnostics and game set-up procedures and ***PLAY THE GAME.*** If it works - don't fix it, just get it out there and

Do it in the dirt!

Please call our Customer Service Department with any questions or comments.

THE TROUBLESHOOTIST'S SECTION

A NOTE ABOUT POWER

DC POWER

The computer board in this machine operates most efficiently when the power supply is providing a steady + 5.20VDC (+0.1VDC). When checking DC power always put your leads across the power inputs on the main board and be sure that the +5 volt supply is between +5.20VDC and +5.24VDC. Also be sure that there is less than .005 volts AC riding on the +5 volt line. If you do find AC on the DC line, suspect the filter capacitor or the rectifier on the power supply. Low voltage and AC on the DC lines are the main causes of the following problems:

* "Garbage" on the screen.
* Computer "Freeze".
* Coin or Coin Meter malfunction.
* A variety of seemingly unrelated problems.

AC POWER

Connect this game only to a grounded three-wire outlet which provides between 108 and 132 volts AC. If you have only a two-wire outlet we recommend that you hire a licensed electrician to install a grounded outlet. The possibility exists that players may receive an electrical shock if this system is not properly grounded.

OUR SERVICE DEPARTMENT

For parts, service, and technical information first contact your authorized Leland Corporation distributor. For additional technical aid feel free to contact the Leland Corp. Customer Service Department at ***(619)562-7000*** Monday through Friday from **8:00 AM to 5:00 PM Pacific Standard Time.**

To provide you with the quickest possible response to your questions, please have the following information ready when you call:

1. **Your game name and serial number.**

2. **Any reference materials and a list of observations.**

TROUBLESHOOTING FLOW CHART

DON'T TOUCH THAT SWITCH !!!

Before you reach for the power switch take a good look at the game. Open it up and check for loose wires, bad connections, or burned spots. Look for spilled drinks and signs of vandalism. Those quick checks will save you a lot of time.

After you've eliminated the obvious, start digging.



Never take anything for granted. This is easy to do if you are in a hurry --- You'll kick yourself every time for missing a broken wire or loose connector after spending hours looking in the wrong place - I have.

GENERAL SHOOTING

GARBAGE
Check: Power supply voltages.
Closed switches on the control panel or coin door.
Loose connections, loose IC's, or bent pins on the board.

NO SOUND
Check: Loose connections.
Low +12VDC supply.
Bad speaker or volume pot.

NO CONTROL OR FUNCTION SWITCHES (Includes coin switches)
Check: All Connections. (Especially ground)
Wire continuity between board and switch.
Closed or broken switches.
Input buffers. (See BUFFERS.)

MONITOR SHOOTING

NO PICTURE
Check: Power connection.
Monitor fuses.
Video connections. (Check continuity.)

SYNC PROBLEMS
Check: Sync and ground connections. (See WIRING DIAGRAM)
Sync polarity.
Video output buffer.

BUFFERS

An input or output (I/O) buffer is the component that connects the actual game computer to the outside world and, as such, is the part most likely to fail. Check the following list when attempting to isolate possible problems. First and second choices are given. (M=Main Board, I/O= Multi-Function Board.)

NOTE: ANY UNAUTHORIZED BOARD REPAIR OR ATTEMPTED REPAIR WILL VOID YOUR WARRANTY.

PROBLEM AREA	COMPONENT	PCB LOCATION
VIDEO (Colors or Sync)	1st 7405 or 74S05	M-U24
	2nd 74LS374	M-U37
PLAYER CONTROLS and/or COIN CONTROLS	1st 150 ohm resistor pack.	See Wiring Diagram & Schematics for specific switch.
	2nd 74LS257	
AUDIO (Bad channel)	1st 7524	I/O-U35(ch5) through U40 (ch0)
	2nd 7533	I/O-U31

ABOUT MECHANICAL COIN COUNTERS

We have <u>not</u> installed mechanical coin counters on this game for two reasons:

1. The bookkeeping program is extremely accurate and includes not only number of coins dropped and dollars earned but also the number of tests and coins in a given period. (See BOOKKEEPING in the DIAGNOSTICS section.)
2. These mechanical coin counters produce an inductive "kick" that ***will*** damage components on the circuit board.

Checkerboard video is the most common problem. If this is, in fact, your problem - take a look at the "NMI not" signal on the master Z80 (pin 17). If a low output is observed, try replacing U114 (74LS08) and/or U119 (74LS157).

NOTE: If you must install a mechanical coin counter, please use the following diagram. (Diodes may be 1N4001 to 1N4004.)



"Ivan IRONMAN Stewart's *SUPER OFF-ROAD*"™
ILLUSTRATED PARTS LIST



OTHER PARTS

CONTROL PANEL

PANEL TOP OVERLAY 22-14924-01
SUB-PANEL OVERLAYS
RED - 22-14921-01
YELLOW - 22-14922-01
BLUE - 22-14923-01

BUTTON - MICRO 2ea
RED - 37-11194-01
YELLOW - 37-11196-01
BLUE - 37-11195-01

LATCH 11ea - 20-10867-01
(7 inner panel and 4 cabinet)

STEERING ASSEMBLY

METAL PANELS
RED 20-13549-01
YELLOW 20-13550-01
BLUE 20-11551-01

ENCODER WHEEL
25-11007-01
LARGE GEAR 25-11008-01
SMALL GEAR 25-11009-01

MISCELLANEOUS

ON/OFF SWITCH - 37-10894-01
VOLUME POT - 51-12501-01
LEG LEVELER - 20-13530-01

PEDAL ASSEMBLY

SHOULDER BOLT
4"X1/2" STAINLESS
25-18251-01
POTENTIOMETER
51-12502-01
ARMATURE
20-13540-01
SPRING - 20-15061-01

ELECTRONICS

PCB ASSEMBLY COMPLETE
38-11695-22
MAIN (BOTTOM) PCB
81-12170-14
MULTI FUNCTION #2 (TOP) PCB
81-18002-22

STEERING OPTO COUPLER PCB
80-20000-01

POWER SUPPLY

ISOLATION TRANSFORMER
43-11704-01
SWITCHING POWER SUPPLY
82-12150-01
LINE FILTER - 63-12131-01
POWER CORD - 87-12143-01

MAIN WIRING DIAGRAM (MAIN BOARD)



NOTE: SYSTEM PIN-OUT OPPOSITE OF PIN-OUT MOLDED IN HARNESS CONNECTORS.

CP-5 SP-5





MALE MOLEX CONNECTORS
TYPICAL PIN-OUT



STEERING WHEEL
CONNECTOR

SEE MAIN BOARD LAYOUT
FOR BOARD CONNECTOR
LOCATIONS.

MAIN WIRING DIAGRAM (MULTI-FUNCTION BOARD)









STEERING OPTO-COUPLER PCB CONNECTION

FOOT PEDAL POTENTIOMETER HOOK-UP



CABINET WIRING DIAGRAM



BOOKKEEPING AND DIAGNOSTICS SECTION

To enter the Bookkeeping and Diagnostics Section:

* With the **Blue Nitro** button depressed, press the **Test** button located inside the front door on the left.

Upon entering the program, the **Main Menu** will appear (Figure 1). Follow the instructions on this menu to select and enter the desired function.

Bookkeeping (Figure 2)

The Bookkeeping function is your game accountant. It records the life-time earnings of your game and allows you, through the use of resettable "Period" totals to keep track of weekly, monthly, or location earnings. This function also separates the readings by coin mech. If one of the coin mech readings is disproportionately low, you may suspect that your players are having trouble with either that mech or the controls of the car associated with that mech.

NOTE: The **"SET COINS/TOKENS PER DOLLAR"** category must be set to the location standard to maintain accurate accounting data. (i.e. 6 COINS/TOKENS PER DOLLAR.)

THIS FUNCTION DOES NOT AFFECT THE NUMBER OF COINS PER CREDIT - SEE THE "GAME SET-UP" SECTION FOR COINS PER CREDIT INFORMATION.

Diagnostics (Figure 3)

You will notice the Diagnostics Section has a sub-menu of its own. Invoking the Diagnostics function will open a complete and easy to use set of tests designed to take the grumbling and hair pulling out of adjusting, troubleshooting, and servicing your machine.

Buttons and Controls Test (Figure 4)

This test provides a quick examination of the state of all buttons and controls as well as an easy range and direction setting format for the steering and pedal controls. As shown on the screen, the **minimum** setting for any foot pedal assembly is between **0 and 80**. Each pedal must also be able to achieve the **maximum** setting of **255** when fully depressed.

Processor Memory Test (Figure 5)

The Erasable Programmable Read Only Memory (EPROM) and Random Access Memory (RAM) IC's are storage areas for the actual game guidelines and are accessed by the Microprocessor section.



FIGURE 1



FIGURE 2



FIGURE 3



FIGURE 4



FIGURE 5



FIGURE 6

Processor Memory Test (cont.)

The percentage of field failures in these areas is very low, but when a problem does arise, it can be a bear to track down. This test samples the action of the processor section and notes any incongruities.

WARNING: **READ YOUR WARRANTY BEFORE ATTEMPTING *ANY* PRINTED CIRCUIT BOARD REPAIRS.**

Video Alignment Screens

The picture on the screen is the most important and most neglected part of the game. It is a proven fact that a dirty, misaligned, or unfocused screen will cause a player to walk away even if the game is his/her favorite piece. A little elbow grease and a couple of minutes spent going through these adjustment screens will make a big difference in the cashbox. Use all three screens to adjust your picture and then go to the "Background Screens" section to make the game look ***"rich"***.

Cross-Hatch Screen (Figure 6)

Used to adjust focus, alignment, size (note x's in the corners) and contrast. Wavy vertical lines (see inset) denote bad contrast. The background should be black and the lines solid white.
If there appears to be an area of color on the screen (usually in one of the corners), your monitor probably needs "degaussing". This condition is caused by moving the game with the power on. Although the monitor contains an internal degaussing mechanism, this mechanism might take a while to work and may not completely cure the problem. I recommend that you purchase a "degaussing coil" and carry it in your service vehicle. Degaussing doesn't take much time and it makes a big difference.

Red and Green Screen (Figure 7)

Adjust the screen or brightness control so the green color bar shows **faintly** on the **1** level and use the red cutoff control to adjust the red bar to the same intensity.

Blue and Miscellaneous Screen (Figure 8)

Use the blue cutoff control to make the gray color appear gray (not brownish). Adjust the red and green drive controls slightly, if necessary, to make the white block white.

Audio Subsystems Test (Figure 9)

The sounds are the second most important feature of any game and in a game like "Super Off-Road" are essential to the feel of the game. The volume of sound is, for the most part, dictated by the location and is thus a "given" but the quality of sound is a function of the program. This test will be of help in your quest to find those "odd" sounds or to remedy the lack of certain sounds.



FIGURE 7



FIGURE 8

Background Screens (Figure 10)

In this test, the background screens are shown while the EPROMs which contain the information for these screens are displayed at the top of the picture. This test is not only helpful when looking for those "glitches" one sometimes encounters, but may also be viewed as a visual test of the colors and picture clarity after the "Video Alignment" test has been completed.

Game Set-Up (Figure 11)

The "Game Set-Up" or "Operator Adjustable" section is vital to the condition of your cash box. When used in conjunction with the "Bookkeeping" and "Statistics" sections of this diagnostics package, the "Game Set-Up" function will keep this game on your list of top earners for years to come.

The **Coins-per-Credit** settings range from 1 coin for 1 credit to 20 coins for 20 credits. *(0 coins for 1 credit sets the game on "free play".)*

SOME SOUND ADVICE:

THOSE ANNOYING ATTRACT MODE SOUNDS ARE SUPPOSED TO DRAW ATTENTION.

LET THEM !

The **Difficulty** level may be set from 1 to 8. Our tests show that level **4** is the best all-around starting point.

After entering their initials and birth date each player is asked to choose the country for which he/she will race. The operator may select one of the countries listed to better suit his game to a particular location.

Game Statistics (Figure 12) **& Game Duration Statistics** (Figure 13)

These two sections are your game "Report Card". Check these sections for glaring discrepancies. Many "starts" and few "joins" or "continues" on any one car could be an indication of a control or coin mech problem.

Unlike many games, whose best income is a result of a 2 to 2.5 minute average game time, collections from ***"SUPER OFF-ROAD"*** **TM** are highest when the average game time is between 3.25 and 3.75 minutes. Your players get more for their money!

Country Selection (Figure 14)

When a player begins a game, he or she is given a choice of countries for whom he or she will race. This section allows you to further customize your game by choosing which eight countries will appear on the country selection screen. You may also choose a preselected list of American or European countries.



FIGURE 9



FIGURE 10



FIGURE 11



FIGURE 12



FIGURE 13



FIGURE 14


REV A
SERIAL #
PART #80-18002-01
Z80 CPU
80186
RAM
27512
SOCKET
74HCT374
74HCT373
74HCT138
74HCT175
74HCT174
74HCT125
74HCT4051
74LS244
7524
7533
8254
RGS-18
RGS-19
RGS-20
RGS-21
RGS-33
RGS-35
RGS-36
RGS-37
RGS38-01
RGS39-01
RGS40-01
BATTERY
7812
0820
1221
J1
J2
J3
J4
J5
J6
J7
J8


U53:D 74A588
U53:C 74A588
U53:B 74A588
VCC
J2 Z48PIN
U67 Z888CPU
CLK
BUSACK
BUSREQ
RESET
NMI
INT
WAIT
HALT
RFSH
WR
RD
IORQ
MREQ
M1
/POR
/RFSH
/2WR
/2RD
/2IORQ
/2MREQ
U58 27512
U59 27512
U57 27512
U56 27512
U61 6264
U60 6264
/COMRD
/2RD
/2WR
/CS4
/CS3
/CS2
/CS1
/CS6
/CS5
POW
C76 0.1UF
C75 0.1UF
ZD0-ZD7
AD0-AD15
U38 74HC374
U23 74HC374
U39 74HC374
U37 74HC374
SEL5
SEL6
SEL7
/CONWR
ZA0-ZA15
U54 RG541
/RFSH
/2MREQ
/2RD
/CS1
/CS2
/CS5
/CS6
/EXP
R65 160 OHM
R64 160 OHM
BT1 3 VOLTS
U52 DS1221
VB1
VB2
VOUT
/CE0
/CE1
/CE2
/CE3
/RST
/RD
/WR
D/Q
U55 RBS39
/2IORQ
/EXP1
/OPT
SEL5
SEL6
SEL7
INT BUS
Title
THE LELAND CORPORATION
Size B
Number 81-18002
Revision A
Date: 8-SEP 1988
Sheet 1 of 10
File: mlfnc/1
Drawn By: ERIC M


THE LELAND CORPORATION
81-18002
Revision A
Sheet 2 of 10
Drawn By: ERIC H.
Date: 8-SEP 1988
File: p1/fnc2
J1 40PIN
U1 Z80BCPU
U18 74LS374
U6 82S18
U2 27512
U3 27512
U4 27512
U5 27512
U7 27512
U8 27512
C12 0.01uF
C13 0.0047uF
R1 330 OHM
VCC
/SRD
SPA15


ZD0-ZD7
/OPT
ZA0-ZA15
J6
10PIN
R77
160 OHM
C127
.001 uF
C126
.001 uF
C125
.001 uF
C124
.001 uF
C123
.001 uF
C122
.001 uF
C121
.001 uF
C120
.001 uF
C119
0.1 uF
CR9
IN4003
RP12:H
RP12:G
RP12:F
RP12:E
RP12:D
RP12:C
RP12:B
RP12:A
RP13:H
RP13:G
RP13:F
RP13:E
RP13:D
RP13:C
RP13:B
RP13:A
10K OHM
100K OHM
RP11:H
RP11:G
RP11:F
RP11:E
RP11:D
RP11:A
RP11:B
RP11:C
1.2K OHM
RP10:H
RP10:G
RP10:F
RP10:E
RP10:D
RP10:A
RP10:B
RP10:C
20K OHM
RP9:H
RP9:G
RP9:F
RP9:E
RP9:D
RP9:A
RP9:B
RP9:C
U77:C
U77:D
U77:A
U77:B
U76:B
U76:C
U76:D
U76:A
LM339
LM339A
U74
RGS18
U75
RGS19
U82
RGS20
U81
RGS21
VCC
/OPT
2A0
2A1
CLK
OE
THE LELAND CORPORATION
Size
B
Number
81-18002
Revision
A
Date: 13-SEP 1988
Sheet 3 of 10
File: a:lfnc/2
Drawn By: ERIC H


THE LELAND CORPORATION
81-18002
Revision A
Sheet 4 of 18
Drawn By: ERIC H
ZD0-ZD7
U70
74LS244
U69
74LS244
/B11
/B12
C182
C183
C184
C185
C186
C189
C188
C187
C92
C93
C94
C95
C96
C99
C98
C97
RP7
150 ohm
RP5
150 ohm
RP6:A
RP6:B
RP6:C
RP6:D
RP6:E
RP6:F
RP6:G
RP6:H
RP4:A
RP4:B
RP4:C
RP4:D
RP4:E
RP4:F
RP4:G
RP4:H
4.7k ohm
VCC
J4
J3
16PIN


C55
20pF
C54
20pF
Y1
16.000MHZ
8MHZ
A1-A16
AD0-AD15
U29
80186
U43
RG536
U44
RG535
U42
RG537
U16
74HCT373
U28
74HCT373
U45
74HCT174
WP2
DIPSHNT
WP1
DIPSHNT
MEMSEL
VCC
GND
/INTRD
/ALE
/CLRINT
4MHZ
/CONRD
/CONWR
/WRL
/WRH
/DAC
/INT
/RES
/TEST
/CONDAC
/RAM
P27
P1
H27
H1
R23H
R23L
THE LELAND CORPORATION
81-18002
Size B
Revision A
Date: 14-SEP 1988
Sheet 5 of 10
File: MLTFNC/5
Drawn By: ERIC H


AD0-AD15
A1-A16
MEMSEL
/RD
/WRL
/WRH
U27
27512
U26
27512
U25
27512
U24
6264
U15
27512
U14
27512
U13
27512
U12
6264
/RDNL
/RDNH
/RD
/WRN
/RAM
CE
OE
CS2
VCC
THE LELAND CORPORATION
Size
B
Number
81-18002
Revision
A
Date: 13-SEP 1988
File: MEMORY.A
Sheet 6 of 10
Drawn BY: ERIC M


AD0-AD15
A1-A16
U11
74LS138
VCC
/WRH
/DAC
U17
74HC374
U18
74HC374
U19
74HC374
U28
74HC374
U21
74HC374
U22
74HC374
C26
10.0uF
C27
10.0uF
C28
10.0uF
C29
10.0uF
C30
10.0uF
C31
10.0uF
REF0
REF1
REF2
REF3
REF4
REF5
Title
THE LELAND CORPORATION
Size
B
Number
81-18002
Revision
A
Date: 13-SEP 1988
Sheet 7 of 10
File: alfpc27
Drawn By: ERIC M


A1-A16
AD0-AD15
/DAC 4 /URL 5
U30 74LS138
U31 74HC374
U32 74HC374
U33 74HC374
U34 74HC374
U35 74HC374
U36 74HC374
U46 AD7524
U47 AD7524
U48 AD7524
U49 AD7524
U50 AD7524
U51 AD7524
VCC
REF1
REF2
REF3
REF4
REF5
REF6
OUT1
OUT2
OUT3
OUT4
OUT5
OUT6
THE LELAND CORPORATION
81-18002


AD0-AD15
A1-A16
ZD0-ZD7
U41
8254
U42
8254
U62
74HCT374
U63
74HCT374
U64
AD7533
U65
74175
U66
74175
U72
ADC0820
U73:C
74LS126
U80
4051
U71
74LS174
U68
RG540
U84
LM7812CT
J5
12PIN
J8
18PIN
J7
18PIN
4MHZ
/CDACWR
COMDAC
/RDY
/ADRD
/CNVT
/ADDR
/PDR
ZA8-ZA15
R63
75Ω
R62
56
R75
75Ω OHM
R76
1.2K OHM
R85
10K OHM
C112
1000pF
C129
0.1uF
C128
0.1uF
C130
10.0uF
CR10
IN4003
CR8
CR7
CR6
CR5
CR4
CR3
CR2
CR1
IN5231
W1
W2
W3
TP1
TP2
TP3
TP4
TP/I
THE LELAND CORPORATION
81-18002
Size
B
Number
Revision
A
Date: 14-SEP 1980
Sheet 9 of 18
File: mitinc/9
Drawn By: ERIC H


THE LELAND CORPORATION
81-18002
A
14-SEP-1988
Sheet 10 of 10
C:\LC\M


P2 - 2 PIN CONN, MOLEX 09-88-1021
P1 - PIN 6, KEY PIN: OMIT
P3 - PIN 4, KEY PIN: OMIT
C8 2200 µF 25V
C11 470 µF 35V
C10 10µF
C88 10µF
C16 0.1µF
C17 470µF 35V
C19 470µF 16V
C18 0.1µF
C14 10µF
C13 0.1µF
SW1 RESET
Q1 2N3904
THM 6072(B)
U122 7805
U123 7815
U109 6116/4016
VR1 5KP
P4 - 10 PIN CONN MOLEX 09-88-1101
RP3 - SIP, 4.7Ω
RP6 - DIP, 100Ω
C89-94, 0.01µF
P5 - 10 PIN CONN MOLEX 09-88-1101
RP4 - SIP, 4.7Ω
RP7 - DIP, 100Ω
C95-101, 0.01µF
P6 - 10 PIN CONN MOLEX 09-88-1101
RP5 - SIP, 4.7Ω
RP8 - DIP, 100Ω
C102-109, 0.01µF
IN4148 OR IN914
U1 Z80-B SOCKET
74LS04 U12
74LS74 U25
Y1 14.8131 MHz
C1 680pF
U99 Z80-B SOCKET
74S04 U110
Y2 12.0000 MHz
C2 680pF
Q2 2N3906
C23 10µF
C115 33pF
8. SYMBOL ▭ IS A 0.01µF MONOLITHIC CAPACITOR
7. RS6 AND RS8 MAY BE 1/4 W
6. SYMBOL ▦ IS JUMPER PACK, TYP. PINOUT (JP1-3)
5. VR1 - VOLUME POT, INSTALL EITHER STAND-UP OR LAY-DOWN (BOTH SHOWN)
4. SYMBOL @ IS TESTPOINT (TP1 - TP7)
3. SYMBOL ( ) IS 0.1µF 50V DISC CAPACITOR (C27-C35)
2. SYMBOL + ○ IS 10µF 16V ELECTROLYTIC RAD. CAP (C22-26)
1. RESISTOR VALUES ARE OHMS, RESISTORS ARE 1/4W, 5%
NOTES: UNLESS OTHERWISE SPECIFIED
NOTES UNLESS OTHERWISE SPECIFIED
REVISIONS
REV | DESCRIPTION | DATE | APPROVED
DWG TITLE MAIN LOGIC CINEMAT SYSTEM PCA
DWG NO 81-12170-12
REV A
SIZE D
SCALE FULL
SHEET 1 OF 1


THE LELAND CORPORATION
MASTER CPU
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 1 OF 18
Z-80B
U99
U113
U96
U110
U111
U112
U100
U54
RS3 330
RS4 330
RS5 330
Y2 12.0000MHZ
C2 680pF
JP3
/SCLK[5]
[8] VBLANK
/MIOREQ[3]
/MRD[2,8,12]
/MWR[2,3]
/MPROM0[2]
/MPROM1[2]
/MPROM2[2]
/MPROM3[2]
/MPROM4[2]
/MPROM5[2]
/MPROM6[2]
MPA13[2]
/COLWR[12]
/MPLDL[3,10]
/MPLDH[3,10]
/MPCLK[10]
/MRAM0[2]
/MRAM1[2]
/COLSEL[12]
/MRH[9]


[1] MPA13
[1] /MPROM4
[1] MADD
+5
[1] /MRD
[1] /MWR
[1] /MPROM5
[1] /MPROM6
[1] /MRAM0
[1] /MRAM1
[1] MDATA
[1] /MPROM0
[1] /MPROM1
[1] /MPROM2
[1] /MPROM3
27128
6116
U101
U102
U103
U104
U105
U106
U107
U108
U109
THE LELAND CORPORATION
TITLE
MASTER CPU PROM/RAM
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 2 OF 10


THE LELAND CORPORATION
TITLE
MASTER VIDEO DATA LATCHES
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 3 OF 18
LS154
RGS-02
LS08
LS374
/MIOREQ
/MRD
/MWR
/MPLDL
/MDS
/MPCSEI
/MVWR [9]
/MVRI [1]
/MIL [9]
/6IN0 [4]
/6IN1 [4]
/6IN2 [4]
/1GID [18]
/MCONT [4]
/0GIA [18]
/0GID [18]
/BKXL [13]
/BKXH [13]
/BKYL [14]
/BKYH [14]
VD15
VD14
VD13
VD12
VD11
VD10
VD9
VD8
VD7
VD6
VD5
VD4
VD3
VD2
VD1
VD0


RP4 4.7
RP5 4.7
RP3 4.7
P5
P6
P4
LS257
U118
U117
U119
LS374
U121
LS32
U97
U120
LS08
U114
LS74
U115
COIN 1
#1 STRT
COIN 2
#2 STRT
SERVICE
[1] MA4
[3] /GIN0
[5] /SHALT
[3] /GIN1
[3] /GIN2
[3] /MCONT
[1] MDATA
/SINT [5]
/SNMI [5]
/SRESET [5,7]
WCOL [1,12,15,16]
/WCOL [12]
/NNMI [1]
THE LELAND CORPORATION
TITLE
GAME INPUT/OUTPUT
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 4 OF 18


THE LELAND CORPORATION
SLAVE CPU
TITLE
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 5 OF 10
Z-80B
LS138
LS244
LS245
RGS-03
JP1
U1
U2
U12
U13
U15
U16
/SCLK
/SRESET
/SNMI
/SINT
/SHALT [4]
/SIOREQ [7]
/SPA13 [6]
/SPROM0 [6]
/SPROM1 [6]
/SPROM2 [6]
/SPROM3 [6]
/SPROM4 [6]
/SPROM5 [6]
/SPROM6 [6]
/SINC [7]
/SURI [7]
/P0 [9]
/ULINE [7]
/SBANK [7]
/SRH [9]
/SPLDH [7,10]
/SPLDL [7,10]
/SPCLK [10]
/SRAM0 [6]
/SRAM1 [6]
/SRD [6,7]
/SWR [6,7]
SA0 [6,7,9]
SA1 [6,7,9]
SA2 [6,9]
SA3 [6,9]
SA4
SA5 [6,7]
SA6 [6,7]
SA7 [6,7]
SA8 [6]
SA9 [6]
SA10 [6]
SA11 [6]
SA12 [6]
SD0 [6,7,10]
SD1 [6,7,10]
SD2 [6,7,10]
SD3 [6,7,10]
SD4 [6,7,10]
SD5 [6,7,10]
SD6 [6,7,10]
SD7 [6,7,10]


[5] SPA13
[5] /SPROM4
[5] SADD
[5] +5
[5] /SRD
[5] /SWR
[5] /SPROM5
[5] /SPROM6
[5] /SRAM0
[5] /SRAM1
[5] SDATA
[5] /SPROM0
[5] /SPROM1
[5] /SPROM2
[5] /SPROM3
27128
6116
U7
U8
U9
U10
U11
U3
U4
U5
U6
THE LELAND CORPORATION
TITLE
SLAVE CPU PROM/RAM
SIZE
B
CODE
NUMBER
REV
A
DATE 2-13-85
SHEET 6 OF 18


THE LELAND CORPORATION
TITLE
SLAVE VIDEO DATA LATCHES
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 7 OF 18
U17
RGS-04
U18
U19
U20
U21
RGS-05
IS374
IS244
U29
U53
S74
/SVRI [5]
/SVWR [9]
/SPB [5]



THE LELAND CORPORATION

TITLE: VIDEO TIMING

SIZE	CODE	NUMBER	REV
B			A

DATE 2-13-85 SHEET 8 OF 10


THE LELAND CORPORATION
TITLE
VIDEO RAM R/W TIMING
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 9 OF 10
U12
S04
R3 330
R2 330
Y1 14.318MHZ
C1 680pF
U28
S74
U25
LS74
U38
LS10
U41
S02
U40
RGS-09
U26
RGS-10
U27
RGS-11
U39
LS175
U14
U52
LS125
U110
/CASH [11]
/CASL [11]
/RAS [11]
/ROE [11]
/B [10.18]
/SPRSEL [10]
/SPCSEL [7.10]
/SINC [5]
/SDS [7.9]
/HPRSEL [10]
/HPCSEL [9.10]
/HINC [1]
/HDS [3.9]
/P0 [1.5.12]
/P1 [9.10.12]
/P2 [12]
/P3 [12]
/UN3 [11]
/UN2 [11]
/UN1 [11]
/UN0 [11]
DCLK [8.12.16]
/DCLK [8.16]
[10] RA0
[7] N0
[7] N1
[7] N2
[7] N3
[1] /MRH
[3] /MIL
[7] /SI
[9] /P1
[5] /SRH
[1] MA3
[1] MA2
[1] MA1
[1] MA0
[9] /MUWR
[9] /MDS
[5] SA3
[5] SA2
[5] SA1
[5] SA0
[7] /SUWR
[9] /SDS


74LS461
U60
U45
U23
U22
MD0
MD1
MD2
MD3
MD4
MD5
MD6
MD7
SD0
SD1
SD2
SD3
SD4
SD5
SD6
SD7
RA0
RA1
RA2
RA3
RA4
RA5
RA6
RA7
[1] MDATA
[5] SDATA
[9] /MPCSEL
[9] /SPCSEL
[1] /MPCLK
[5] /SPCLK
[1] /MPLDH
[1] /MPLDL
[5] /SPLDH
[5] /SPLDL
[9] /MPRSEL
[9] /SPRSEL
VADD
[11]
[9.11]
+5
RP2
330
LS257
U31
U44
[9] C
[8] VA14
[8] VA1
[8] VA8
[8] VA2
[8] VA9
[8] VA3
[8] VA10
[9] /P1
[9] /B
[8] VA4
[8] VA11
[8] VA5
[8] VA12
[8] VA6
[8] VA13
[8] VA7
1A
1B
4A
4B
2A
2B
3A
3B
SEL
OE
1Y
4Y
2Y
3Y
THE LELAND CORPORATION
TITLE
VIDEO MEMORY ADDRESS MUX
SIZE
B
CODE
NUMBER
REV
A
DATE 2-13-85
SHEET 10 OF 18


[9] /WN0
[9] /WN1
[9] /WN2
[9] /WN3
[9] /CASL
[9] /CASH
[9] /RAS
[9] /RDE
[18] VADD
VDATA
[17]
U32 RP1 12
U32 RP1 14
U32 RP1 11
U32 RP1 10
U32 RP1 9
U32 RP1 15
U32 RP1 13
33
4416-15
U46
U47
U48
U49
U33
U34
U35
U36
THE LELAND CORPORATION
TITLE
VIDEO MEMORY
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 11 OF 18


LS173
U78
U77
U76
U75
LS244
U66
2148
U50
U51
LS374
U37
LS245
U65
LS32
U54
7405
U24
[3.7] VD12
[3.7] VD13
[3.7] VD14
[3.7] VD15
[3.7] VD8
[3.7] VD9
[3.7] VD10
[3.7] VD11
[3.7] VD4
[3.7] VD5
[3.7] VD6
[3.7] VD7
[3.7] VD0
[3.7] VD1
[3.7] VD2
[3.7] VD3
[9] /P3
[9] /P0
[9] /P2
[9] /P1
[4] WCOL
[4] /WCOL
[16] LCA5
[16] LCA6
[16] LCA7
[16] BSV0
[16] BSV1
[16] BSV2
[1] MA6
[1] MA7
[1] MA8
[1] MA9
[1] MA3
[1] MA4
[1] MA5
[1] MD3
[1] MD2
[1] MD1
[1] MD0
[1] MD7
[1] MD6
[1] MD5
[1] MD4
[1] /MRD
[1] /COLSEL
[1] /COLWR
DCL
[9]
CMPBLK
[8]
[8] HSYNC
[8] VSYNC
R6 220
R9 470
R12 220
R15 470
R7 1K
R10 220
R11 470
R14 1K
R13 470
R16 470
R8 470
R5 1K
R4 1K
+5
P1
THE LELAND CORPORATION
TITLE
COLOR RAM / VIDEO OUTPUT
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 12 OF 18


SPARE GATES
LS125
U52
LS125
U52
7405
U24
LS32
U54
RP2
330
RP3
RP3
4.7
RP3
RP3
RP4
4.7
RP5
4.7
+5
LS175
U71
CLR
LS374
U57
OE
74LS461
U56
[3] /BKXH
[3] /BKXL
MD7
MD6
MD5
MD4
MD3
MD2
MD1
MD0
BX2 [8]
BX1 [8]
BX0 [8]
[8] BMCNT
[8] /SRL
BHA7
BHA6
BHA5
BHA4
BHA3
BHA2
BHA1
BHA0
[15]
THE LELAND CORPORATION
TITLE
BACKGROUND HORIZONTAL ADDRESS
SIZE
B
CODE
NUMBER
REV
A
DATE 2-13-85
SHEET 13 OF 18


JP2
BPB [18]
BKA13 [15]
LS138
U55
/BB0 [15]
/BB1 [15]
/BB2 [15]
/BB3 [15]
/BB4 [15]
/BB5 [15]
/BB6 [15]
/BB7 [15]
LS175
U55
[8] /BKYH
LS283
U74
[8] VA14
CA9 [16]
CA8 [15]
BVA7 [15]
LS374
U58
[8] /BKYL
LS283
U73
[8] VA13
[8] VA12
[8] VA11
[8] VA10
BVA6 [15]
BVA5 [15]
BVA4 [15]
BVA3 [15]
LS283
U72
[8] VA9
[8] VA8
[8] VA7
BVA2 [16]
BVA1 [16]
BVA0 [16]
THE LELAND CORPORATION
TITLE
BACKGROUND VERTICAL ADDRESS
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 14 OF 18


THE LELAND CORPORATION
TITLE
BACKGROUND PROMS
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
SHEET 15 OF 18
U68
U70
U92
U98
U67
U69
U89
U91
27128
+5
A0-A7 [15]


THE LELAND CORPORATION
TITLE
BACKGROUND CHARACTER GENERATOR
SIZE
B
CODE
NUMBER
REV
A
DATE 2-13-85
SHEET 15 OF 18


RESET
SW1
RS2
220
1N4148
CR2
C14
10uF
R51
12K
1N4148
CR1
2N3904
Q1
R50
1K
C13
.1uF
+5
POR [1..18]
LS132
U97
LS374
U79
U86
R22
180
R21
390
R20
750
R19
1.5K
R24
3K
R23
6.2K
R18
12K
R17
24K
R28
180
R29
390
R32
750
R33
1.5K
R34
3K
R27
6.2K
R31
12K
R30
24K
R26
470
R36
470
R25
24K
R35
24K
C4
100pF
C3
100pF
LM324
U98
R42
100K
R43
100K
R38
100K
R37
100K
C15
1uF
+12V
DACOUT [18]
P3
+25V
RET
C18
1uF
C19
470uF
C20-26
10uF
C27-84
1uF
7812
U123
IN
OUT
C16
1uF
C17
470uF
+12V
THE LELAND CORPORATION
TITLE
DAC SOUND OUTPUT
SIZE
B
CODE
NUMBER
REV
A
DATE
2-13-85
SHEET
17 OF 18


8910
8912
U86
U87
MD7
MD6
MD5
MD4
MD3
MD2
MD1
MD0
/B
/POR
/LDCL [17]
/MDCL [17]
MPB [1]
BPB [14]
CPB [16]
LS132
U97
/IGID
/OGIA
/OGID
P2
SPEAKER
SPEAKER
C8 2200uF
PS9 NOT INSTALLED
+12V
2002
U122
R58 2.2
R57 200 1/2W
R55 2.2 1/2W
C9 1uF
C11 470uF
C10 10uF
VOLUME
VR01 5KP
R49 24K
C6 NOT INSTALLED
C5 100pF
U98
LM324
R44 24K
R48 100K
C12 33pF
R47 100K
[17] DACOUT
R39 100K
R45 12K
C7 33pF
R46 1K
R40 100K
R41 100K
THE LELAND CORPORATION
TITLE
G1 SOUND OUTPUT
SIZE B
CODE
NUMBER
REV A
DATE 2-13-85
JMW
SHEET 18 OF 18

K7000 COLOR MONITOR SCHEMATIC DIAGRAM




P538
P448
RED
GRN
BLU
CRT
22.5mm NECK
SKT201
P6
J6
P201
GND
BLU
GRN
RED
R30
100
R31
100
R32
100
R33
1K
R34
1K
R35
1K
R27
22K
Q8
C13
22
25V
NTRAST
R207
6.8K,2W
R208
6.8K,2W
R209
6.8K,2W
C204
.01
R210
2.7K,1/2W
R211
2.7K
1/2W
R212
2.7K,1/2W
C203
470
2SC2068
C201
470
Q201
Q202
2SC2068
C202
470
Q203
2SC2068
VR
202
200
VR
204
200
VR
206
200
R201
2.7K
R203
2.7K
R205
2.7K
VR201
2K
R202
150
VR
203
2K
R204
150
VR
205
2K
R206
150
CUT OFF
DRIVE
CUT OFF
DRIVE
CUT OFF
DRIVE
R213
.20 1W
C205
1500
1.5KV
P202
J202
P5
+12V
+130V
F/L
+12V
C45
470
16V
C46
470
16V
C42
1000
16V
C43
.001
D14
R90
1.2, 2W
R92
1.2, 2W
C65
3300
1.6KV
T1
FOCUS
SCREEN
R93
1K,2W
C44
.1, 100V
PP
2SD1398
Q11
R112
0.47
1/2W
C36
4300
1500V
HORIZONTAL
OUTPUT
T2
C32
100
R88
1.8K
C33
.0033
C34
.01
500V
R74
22
C35
.012
R89
3.9K,5W
+24V
R91
1.2, 2W
C48
100
35V
D13
D25
C41
.001
C40
2200
35V
+24V
R96
1.8K
3W
MO
C69
5600
1.6KV
C37
0.15μF
D18
D15
C38
39
200V
PP
R98
2.2K,1W
R99
2.2K,1W
L1
SIZE
ADJUST.
L2
LINEARITY
D16
HOR
POS
D17
R97
270,3W
R95
47K
R94
47K
R83
680
1/2W
R126
820
1/2W
R127
9.1K
Q9
VR3
10K
VERTICAL
POSITION
R100
270,1W
+130V
P4
J4
YEL
BRN
BLU
RED
DEFLECTION
YOKE
R128
10K
1/2W
25K7107